(54) Title: OPTICAL CRITICAL DIMENSION METROLOGY SYSTEM INTEGRATED INTO SEMICONDUCTOR WAFER PROCESS TOOL

(57) Abstract: A wafer measurement station (19) integrated within a process tool (11) has a scatterometry instrument (35) for measuring patterned features on wafers (31). A wafer handler (17) feeds wafers between a cassette (15) and one or more process stations (13) of the process tool. Wafers presented to the measurement station are held on a wafer support (33), which may be moveable, and a scatterometry instrument has an optical measurement system (41) that is moveable by a stage (39) over the wafer support. A window (37) isolates the moveable optics from the wafer. The optical measurement system are microscope-based optics forming a low NA system. The illumination spot size at the wafer is larger than a periodicity of the patterned features, and data processing uses a scattering model to analyze the optical signature of the collected light.

Description

OPTICAL CRITICAL DIMENSION METROLOGY SYSTEM
INTEGRATED INTO SEMICONDUCTOR WAFER PROCESS TOOL

TECHNICAL FIELD

The present invention relates to semiconductor wafer processing for integrated circuit manufacture, and in particular to lithography systems, cluster tool environments, or other wafer process tools which have a robotic handler that transports wafers between the stations or modules of the tool. The invention also relates to metrology equipment for semiconductor wafers, and in particular optical measuring equipment for measuring the parameters of diffractive structures formed during lithography and further processed in other integrated circuit manufacture process steps.

BACKGROUND ART

In semiconductor manufacturing, process tools are used to deposit, planarize, remove and pattern very thin layers of materials on semiconductor wafers in order to make electronic structures. Process tools include deposition tools for depositing uniform thin films onto semiconductor surfaces, lithography tools for applying photoresist material and creating patterns in the resist, etch tools for etching structures into the material layers, polishing tools for removing material and planarizing the wafer, and cleaning tools for removing contamination or leftover material after certain process steps. Cluster tools combine various process stations with handling systems to transfer wafers between stations. For example, lithography tracks are typically multi-station systems with their own robotic wafer handlers for transport between stations within the track. These process tools usually include various sensors, such as thermometers and gas flowmeters, to measure process parameters for controlling the manufacturing process

within certain tolerances. For example, different bake
stations of a lithography track may have different tem-
perature settings at which wafers are held for different
periods of time. Other sensors in a process tool deter-
5   mine a major change in some measurement parameter that is
indicative of process completion, such as motor current
end point in chemical-mechanical planarization (CMP).
Steppers , which are tools for patterning photoresist,
typically have an optical notch sensor for determining
10   the location of a wafer's alignment notch relative to a
reference frame of the stepper tool so that the wafer can
be rotated into a predetermined orientation for properly
aligned exposure of a pattern. The aforementioned sen-
sors are incorporated into the modules or stations and
15   form an essential part of the processing tools themselves
to ensure their proper operation.

          Semiconductor manufacture also makes use of
inspection equipment to look for any defects or anomalies
on a wafer and to report information (location, size,
20   identity, etc.) regarding such defects or anomalies.
Measuring equipment, including various optical measuring
tools, such as spectroreflectometers, , beam profile
reflectometers, ellipsometers, and polarimeters, are used
to characterize the layers and structures formed on a
25   wafer in terms of dimensional parameters such as layer
thickness or line width. It is important to measure
these parameters for process control. While such measur-
ing equipment might report general information about an
entire wafer, particularly when measuring unpatterned
30   wafers, often the measurements need to be collected at
specific predetermined locations on the wafer, particu-
larly when measuring specific features on a patterned
wafer. Because of this need to locate specific features
with high precision for measurements, measuring tools
35   typically employ pre-aligners and stages to align the
wafer with respect to the optical system to allow mea-
surement of various locations on the wafer. Many measur-
ing tools move the wafer laterally (horizontally) while

keeping the measurement system (optics) substantially
stationary. This requires a footprint that is at least
twice the diameter of the wafer in both lateral dimen-
sions, in order to provide full coverage of the wafer.

5   Other measuring tools keep the wafer stationary, and move
some portion of the optics to measure various portions of
the wafer. Typically, an objective lens focuses illumi-
nating light onto the wafer and/or collects reflected
light from the wafer. In some systems the same optical

10   element is used as the objective for illumination and
detection, in other systems, each function is handled
separately, or only one of the two functions are per-
formed. In any case, the objective is used here as the
optics system for illuminating a portion of the wafer and

15   for collecting light from a portion of the wafer. Hence,
some measuring tools move the wafer to position the ob-
jective with respect to the wafer, and some move the
wafer. In traditional semiconductor manufacturing, me-
trology tools, whether inspection equipment or measuring

20   equipment, are stand-alone units. That is, they are
detached from the process tools and are characterized by
having their own load ports for wafer carriers, e.g.
FOUPs or cassettes, generally referred to as "cassettes"
below. They are sometimes even located in a different

25   area of the fabrication facility from the process tool.
In any case, individual wafers or cassettes of wafers
must be transported between the process tool and the
inspection or measurement tool whenever it is desired to
inspect or measure a wafer following some process step.

30   Because of the inherent delays associated with stand
alone tools, inspection or measurement is normally lim-
ited to sampling a small subset of the wafers, or to
sampling a small portion of each inspected wafer. Fur-
thermore, wafers are measured only after a whole set of

35   wafers has been processed, thus putting wafers at risk if
there is a tool or process malfunction. Also, process
tools are often controlled based on the results of the
measurements, and long delays between processing a wafer

-4-

and the availability of the measurements for that wafer
reduces either the effectiveness of the control or the
total rate at which wafers can be processed.

5   Scatterometrty is an optical measurement method
that is advantageous for measuring the results of modern
processes. The lateral dimensions of features on a wafer
are shrinking and becoming small compared to optical
wavelengths and measurement spot sizes. It has become
difficult or impossible to optically image the results of
10   such processes. Electron beams and profilometer-type
instruments (e.g., atomic force microscopes, AFMs) can
"image" such features but are slow and difficult to inte-
grate into process tools. Scatterometry uses the optical
characteristic of a periodic feature to determine parame-
15   ters relating to lateral dimensions. Furthermore, as
light penetrates below the "top" surface of the struc-
tures, scatterometry is sensitive to variations in the
features with depth into the sample. For example, con-
sider a structure that is repeating lines and spaces with
20   a period of 0.2 microns and a nominal duty cycle of 50%.
Nominally the lines and spaces would have widths of 100
nm, which is well below the resolution of an optical
imaging system. However, the characteristic of light
reflected from the structure will depend upon the details
25   of the periodic structure. For example, the lines may
not have vertical walls, and variations in the sidewall
angle will cause variations of the optical characteris-
tics. Scatterometry utilizes some model of the optical
characteristics of the periodic feature which has parame-
30   ters. In scatterometry, the parameters of the modelare
varied until there is a best match between measured and
modeled characteristics. The parameters of the model
that produce the best match are regarded as the measured
parameters. It is clear that the measured parameters can
35   be transformed mathematically to a form that is easier to
use or more closely related to the process.

The optical characteristic used for
scatterometry is measurable and has one or more independ-

ent parameters so that the whole collection of independent parameters forms a plurality. Most measurable optical characteristics are related to the intensity of light that has interacted with a structure. Examples are the

5   intensity of reflected light for a reflectometer, and the ellipsometric parameters psi and delta for an ellipsometer. Examples of independent parameters are wavelength and incidence angle. Other independent parameters are possible, for example azimuthal angle measured

10   relative to some pattern in the structure of interest, or polarization state. In general, an independent parameter is any characteristic of the measurement system which is controlled and which affects the optical characteristic of the wafer.

15   The model used by scatterometry may be either physical or theoretical. In the former case, the "model" consists of measurements of samples with known parameters. Ideally the measurements are made with an instrument that is the same or similar to the measurement tool

20   under discussion. Preferably, the model may be theoretical, and include the optical properties of the instrument as well as some mathematical representation of light interacting with structures having variable parameters. It also includes the optical properties of the material

25   (index and absorbance) as appropriate, e.g., as functions of wavelength.

               The theoretical model typically comprises calculations of electromagnetic interactions that are exact for some model of the structure on the wafer. Typically,

30   the geometric model of the structure is an approximation to a perceived possible geometric model. For example, the profile of the periodic structure is expected to be smooth but the actual geometric model has a "staircase" approximation to allow rigorous coupled mode calculations

35   to be performed. Such calculations are often time consuming. In order to optimize the speed of measurement one can perform some portion of the calculation in advance of the measurements and store the results in a

database. In a simple case, one picks the structure
parameters and fixes the possible values for each parame-
ter based on a range and discretization. Then optical
characteristics for each combination of parameter values
5   is calculated and stored in a database. At measurement
time, each characteristic is compared to a measured char-
acteristic, and the parameters associated with the theo-
retical charcteristic that best matches the measured
characteristic are chosen as the measured parameters.
10   For example, the measured profile has the profile parame-
ters of the best fit model characteristic. Alterna-
tively, the measured critical dimension of the lines is
derived from the parameterized profile, e.g., the width
of the line at 20% of its height. A disadvantage of
15   using a library is that the discretization of the parame-
ters is apparent in the measurements and may lead to
"discretization noise" in measurements of a physically
smoothly varying parameter.

        An alternative to the library approach men-
20   tioned above, is a "library-less" method where electro-
magnetic calculations are performed at measurement time.
A disadvantage to this approach is that there is a trade-
off between the measurement time (which includes calcula-
tion time) and model complexity. For example, the stair-
25   case approximation mentioned above cannot have many steps
in order to finish in an acceptable time, and may not fit
the actual profile very well, or parameterization of its
characteristic may not have the degrees of freedom needed
to match the measured characteristics.

30   Scatterometry is sensitive to overlay registra-
tion. A substructure with a lateral geometry of a cer-
tain period is produced at one state of the wafer.
Later, as the structures on the wafer have been built up,
another sub-structure of the same period may be placed
35   directly over the first substructure. The second sub-
structure may consist of developed photoresist, and the
first substructure of an etched lower layer of the wafer,
for example, etched gate contacts, isolation trenchs, or

metallic wiring. The two substructures now form a single structure with a period that will have an optical characteristic, since they occupy the same lateral region. The alignment between the two substructures will generally

5   affect the (total) structure's optical characteristic, and can be represented by parameters in the model characteristic. Thus scatterometry can measure overlay, by having a properly parameterized model, and returning the value of the parameter(s) related to alignment of the

10   sub-structures. Overlay is a very critical measurement since it is a measure of how well the stepper was able to align and then print one pattern over another. This parameter is tightly controlled because it can have a very significant bearing on how densely features can be

15   packed together as well as the overall performance of the semiconductor device. Thus the same instrument is capable of measuring several critical lithography parameters using scatterometry: overlay, profiles, critical dimensions, line edge roughness, contact hole shapes and

20   whether they are open or not.

Scatterometry can also be applied to make measurements of critical parameters after etch, CMP and Clean. For example, after metal CMP scatterometry can be used to determine the amount of oxide erosion or remain-

25   ing metal in a periodic array consisting of alternating oxide and metal areas, where the lateral dimensions are significantly smaller than the spot size and comparable to the wavelength of light used. If there is (undesirable) metal or other film residue left on these periodic

30   structures, it is possible to detect their presence, again by comparing the measured optical characteristic data to appropriate modeled characteristics.

The structures inspected with scatterometry are typically substantially periodic, but not exactly so.

35   Defects in the materials and process applied to the wafer lead to non-periodic features on structures that are intended to be periodic, for example lines are not perfectly straight and have "roughness".

Substantially periodic structures typically reflect light into various diffraction orders, as is well known in the art. For finer structures, or longer wavelengths or higher orders, a diffracted order may be non-
5   propagating or evanescent, and not detectable directly. However, such non-propagating orders take energy away from propagating orders, and so may affect the characteristic (measured portion) of the propagating orders. Scatterometry is often performed with substantially only
10 the 0^{th} diffracted order contributing to the measured characteristics, since it never becomes evanescent. In European patent application publication EP 0 973 068 A2 (Nova Measuring Instruments), Cohen et al. describe a measuring tool that is integrated into a lithography
15 track, or alternatively as one of the components of a cluster tool. The measuring tool is a spectrophotometer for measuring thickness, absorption coefficient and refractive index of the photoresist, and substrate reflectivity. Measurement occurs after the resist coating step,
20 but prior to the exposure and development steps. The measurement results are used in forward control of the exposure tool to achieve an optimum exposure dose. However, neither critical dimension metrology of the patterned structures nor overlay is integrated into this
25 phototrack and would still typically be conducted after the development step using a stand-alone machine.

In European patent application publication EP 0 973 069 A2 (Nova Measuring Instruments), Dishon et al. describe a lithotrack apparatus into which a measuring
30 station is integrated, using the same robotic wafer handler. The measurement instrument consists of a microscope with a high magnification high NA image channel for measuring critical dimension (CD) errors, etc.. The wafer is held stationary while in the measuring station
35 and the station has a movable optical head on an x-y-z stage. The optical head and movable stage are in an enclosure with a transparent optical window in order to protect the wafer from contamination. Measurement occurs

at the end of lithographic processing before being un-
loaded to a cassette.

DISCLOSURE OF THE INVENTION

5   The object is met by a wafer measurement system
and method in which an optical scatterometry measurement
station is integrated into a wafer process tool. The
measurement station makes use of the the robotic wafer
handler mechanism of the process tool, for wafer transfer
10   within the process tool between stations or modules in-
cluding the receipt by the measurement station of wafers
to be measured. Wafers can thus be transferred directly
from a processing station of the process tool to the
measurement station without first having to leave the
15   process tool. Thus it is convenient to measure the pro-
cess results on individual wafers before all the wafers
in the set have been processed. At the time of measure-
ment, processing of a wafer may be complete, so that the
wafer is then transferred by the wafer handler to a car-
20   rier or cassette station associated with the process
tool. Alternately, wafers may be measured at an interme-
diate stage of processing with subsequent processing
depending on the results of the measurements. When pro-
cessed by other modules of the process tool, the process
25   parameters may depend upon the measurement result. In
some cases the wafer may be reworked by the same process
module if the result of an earlier process is found by
the measurement to be inadequate. Since measurement
results are available more quickly than with stand alone
30   metrology, equipment efficiency is improved and closed
loop process control is now possible.
          The measurement station comprising an optical
instrument that obtains data for an optical characteris-
tic of a diffractive pattern on a wafer.. The instrument
35   preferably uses a movable optical system to position the
measurement location on the wafer with minimal motion of
the wafer, to allow the minimum footprint of the measure-
ment station. A wafer support preferably holds the wafer

-10-

in a fixed translational (x,y) position, while the opti-
cal head moves in a plane parallel to the wafer to a
plurality of specified locations over the wafer,. In a
preferred embodiment (r-theta), the wafer rotates (theta,
with substantially no translation), and the optical head
translates in one lateral dimension substantially from
the center to the edge of the wafer, r. In an alternative
embodiment, some translation of the wafer or optics per-
pendicular to r is allowed to simplify the algorithms for
positioning the optics relative to the wafer. The opti-
cal instrument may be a spectro-reflectometer or a beam
profile reflectometer, an ellipsometer, a polarmeter, or
any optical instrument capable of measuring an optical
characteristic of sites on the wafer as a function of
independent optical parameters . Possible independent
optical parameters include polar angle of incidence,
polar angle of reflection, direction of incidence (with
respect to patterns on the wafer), direction of reflec-
tion, wavelength, incident polarization, reflected polar-
ization. "Reflection" is used here and throughout to
signify either reflection from or transmission through a
sample (wafer) of the incident light. The preferred
embodiment is a substantially normal incidence
reflectometer with wavelength as the independent optical
parameter. A light source provides a light beam that is
directed through the head onto the patterned features of
the wafer surface. The optical system typically includes
an objective lens for focusing the light beam to a spot
on the wafer. The objective lens may also act as a light
collector for light reflected from the wafer. The opti-
cal system may have a pinhole associated with the light
collection path, which maintains a fixed optical rela-
tionship to the objective lens as the optical system
moves. In any case, light collected by the optical opti-
cal system is detected and analyzed to obtain a measure
of the parameters of interest of the pattern features in
the wafer. Analysis of the data obtained from the light
detector preferably involves comparison of the measured

characteristic optical signatures from the wafer surface
features with a database of signatures stored in a mem-
ory, each of which is associated with known critical
dimensions of pattern features.

5

BRIEF DESCRIPTION OF THE DRAWINGS
        Fig. 1 is a schematic plan view of a process
tool integrating an optical scatterometry measurement
station (IMS) in accord with the present invention.

10   Fig. 2 is a schematic side view of an optical
measurement station suitable for scatterometry and for
integration with the process tool of Fig. 1.
        Fig. 3 is a perspective view showing details of
the measurement optics for another measurement station

15 suitable for scatterometry and for integration with the
process tool different from the station of Fig. 2.
        Fig. 4 is a schematic side view showing details
of components used in an alternate embodiment of the
measurement optics in Fig. 3.

20   Fig. 5 is a schematic side view showing the
position of components used in another alternate embodi-
ment of the measurement optics in Fig. 3.

BEST MODE FOR CARRYING OUT THE INVENTION
25   With reference to Fig. 1, a process tool 11
includes a plurality of processing stations (PS) 13, one
or more cassette stations (CS) 15, and a shared robotic
wafer handling and transfer mechanism (RH) 17. The ro-
botic handler 17 unloads wafers from the cassette sta-

30 tions 15 and transports the wafers in a specified se-
quence between the processing stations 13 for carrying
out various process steps. The processing stations 13
can be any of a wise variety of tools used in semiconduc-
tor circuit manufacturing, including deposition tools,

35 lithography tools, etch tools, bake tools, planarizing or
polishing tools and cleaning tools. After completion of
the last process step, the robotic handler 17 transports
a wafer from the last processing station 13 back to a

-12-

cassette stations 15, which may or may not be the same
station that the wafer was unloaded from.

In the present invention the process tool 11
also includes one ore more integrated measurement sta-
5   tions (IMS) 19. The measurement station 19 is con-
strained by the size standards in order to permit it to
be mounted in the process tool 11. A measurement station
21 might also replace a cassette load station 15, which
can have even tighter size constraints than the process-
10   ing stations 13. The measurement station(s) 19 or 21
share the same robotic handler 17 as the rest of the
process tool 11. The robotic handler can comprise sev-
eral robots, for moving the wafer both globally and lo-
cally within the process tool 11. At any time in the
15   manufacturing process after completion of any of one or
more process steps in a processing station 13, the han-
dler 17 may transport a wafer to a measurement station 19
or 21 for carrying out a specified measurement. Measure-
ment of a wafer may be done at the completion of all
20   process steps prior to being returned to a cassette sta-
tion 15 or at some intermediate stage in the manufactur-
ing process. Subsequent process steps may depend upon
the measurement results. Also, the processing of subse-
quent wafers may depend upon the measurement results.
25   With reference to a preferred embodiment in
Fig. 2, an integrated measurement station 19 or 21 in the
present invention provides an optical instrument suitable
for scatterometry, e.g., for measuring parameters of fine
patterned features on a wafer, such as line width, step
30   height, sidewall angle or line profile. However, the
process tool 11 in Fig. 1 might also include other kinds
of measurement and inspection stations, such as for char-
acterizing unpatterned wafers (e.g., resist coating
thickness) or measuring electrical characteristics.
35   In the preferred optical measurement station 19
in Fig. 2, a wafer 31 is mounted on a three-point wafer
support 33 and objective 41 preferably moves laterally in
at least one dimension. The support 33 preferably holds

the wafer 31 stationary once it has been placed under-
neath the measurement optics. A three-point support 33
is preferred because it provides minimum wafer contact.
Since the wafer does not move in this preferred embodi-
ment, no interlocks are necessary, thereby preventing
inadvertent collisions between the process tool wafer
transfer mechanism and the wafer support mechanisms.

Alternatively, the three-point support 33 may
be replaced with either an edge support, a wafer chuck or
a multi-pin chuck. In the edge support, the wafer 31 is
centered and supported by its outside edge. In the wafer
chuck, the wafer 31 rests flat on a platen. In a multi-
pin chuck the wafer rests on 3 or more pins, and vacuum
is applied to the pins to hold the wafer firmly, but with
less contact area than a vacuum chuck. All alternatives
allow rotation and/or notch alignment of the wafer 31
after it has been placed into the station. While the
chuck potentially does a better job at keeping the wafer
flat and therefore always in focus relative to the mea-
surement optics, thereby improving throughput since
autofocusing time is minimized, it requires lift pins for
robot and effector clearance between the chuck and the
handler and backside contact with the platen provides an
opportunity for cross-contamination.

The measurement optics 35 are physically iso-
lated from the wafer 31 by an enclosure 36 with a trans-
parent (e.g., fused silica) window 37. The window 37
protects the wafer surface from contamination from any
particles or outgassing originating in the optics assem-
bly above. Likewise, the window 37 protects the optics
from contamination originating from the wafer 31, such as
vapors, or an adverse environment the wafer 31 may be
located in, such as chemicals, liquids, gases or vacuum.

The optics assembly in the enclosure 36 in-
cludes a movable measurement optical system 35 driven by
a moving stage 39. The purpose of the stage system 39 is
to move the optics over the wafer to a location selected
for measurement. Accurate positioning of the objective

-14-

41 with respect to the wafer is important since the wafer features to be measured are small and in specific locations.   In a preferred embodiment, the stage system 39 consists of x and y stages for moving the objective in

5   two orthogonal lateral directions parallel to the wafer surface.   Alternatively, the objective could be moved by a single stage in one direction (a radial direction) only, while the wafer is rotated, for examples, by an edge support, a pin-chuck or a platen.   - A variety of

10   such stage systems 39 are available within the size constraints imposed by the process tools.   Moving the optical measurement system 35 avoids having to translate the wafer, which would require a bigger footprint, while still providing full wafer coverage.

15   The movable optical system 35 includes at least objective lens 41 and pinhole 43 in fixed relationship to each other.   The objective lens 41 is in both the incident and reflected light paths.   The objective lens 41 focuses incident light 45 through the window 45 onto the

20   structured surface of the wafer 31.   The objective lens 41 also collects the light reflected from the wafer and focuses some of this collected light 47 onto the pinhole 43.   The pinhole 43 samples the light 47 for transmission to a spectroscopic detection system (not shown in Fig.

25   2), elements of which may or may not be part of the movable optical system 35.

      Fig. 3 shows further details of another preferred optical measurement instrument.

      In this case, some of the optics on support 35a

30   move only in y on ystages 39a which are attached to the top of enclosure 36.   Support 35b and its optics move in y with support 35a, but also move in x on xstages 39b. Thus in this embodiment the objective 41 moves in x and y, and the pinhole in mirror 43 moves only in y, so the

35   two are not in a fixed relationship.   In this embodiment light from broadband light source 51 is conveyed to optical measurement station 19 by fiber 53.   A broadband light source 51 provides electromagnetic radiation

-15-

(light, both visible and ultraviolet) at a multiplicity
of wavelengths, preferably in a 240 nm - 1000 nm wave-
length range. Collimator 55 collects and substantially
collimates light from fiber 53. Mirror 57 deflects the
5   collimated beam towards the x-y movable optics. Beam
splitter 59 splits collimated beam 56 into monitor beam
62 and sample beam 64. Monitor beam 62 is deflected by
mirrors 61a and 61b so that it can be focused by monitor
lens 61c onto monitor pin-hole mirror 61d. Some of beam
10   61 is sampled by the pinhole and passes through a fiber
to monitor spectrometer 61e where its spectrum is re-
corded. Objective 41 focuses the downward propagating
illuminating light 64a onto wafer 31, through window 37
held by frame 36, and collects reflected sample beam 64b.
15   Transparent window 37 is attached to the bottom of the
enclosure 36 over wafer 31. Sample beam 64 passes
through beam splitter 59 and is deflected by mirrors 63a,
63b and 63c. Sample lens 63 d focuses sample beam 64b
onto sample pinhole mirror 43, which samples part of
20   sample beam and passes it through a fiber to spectrometer
61e. Sample pinhole mirror 43 reflects the remainder of
sample beam 64 so that it can be focused by imaging lens
63e onto small field of view camera 63g.

     Reference reflector 32 is in the range of mo-
25   tion of the objective but not obscuring the wafer. It
has a stable reflectivity, and the effective reflecting
surface has nominally the same z position as the top of
wafer 31.

     Absorber 34 is designed to reflect nearly zero
30   light when the objective is placed over it. The absorber
could be any number of things including: a reasonably
black surface far from focus, two black surfaces in a V
shape, a stacked array of razor blades, or a roughened
black-painted surface. The best design is two or three
35   pieces of black glass arranged so the specular reflection
from one falls on the next. With the objective placed
over the absorber is possible to measure the signal due
to unwanted stray light in the optics so that this quan-

tity can later be subtracted from each measurement.
Preferably, the absorber 34 is positioned so the objec-
tive 41 views it through the window 37 or, if this is not
mechanically feasible, a second window (not shown) that
5   has the same reflectance as window 37.In order to view a
large patch near the center of the wafer, support 35b
moves to the postion shown. LED 71 emits large-field-of-
view (LFOV) illumination 72.   Fresnel lens 73 collects
LFOV illumination 72 and directs it towards LFOV beam
10   splitter 59. LFOV beam splitter 75 directs some illumi-
nation onto wafer 31 and allows some light reflected by
the wafer to pass through LFOV lens 77 which focuses onto
LFOV camera 79.   The LFOV is at least 2 mm square.

        Spectrometers 61e and 63f, cameras 79 and 63g,
15   x nd y motors (not shown) associated with stages 39a and
39b, etc are electrically connected to the measurement
processor (not shown). The processor digitizes spectra,
drives motors, and generally controls the system to col-
lect characteristics at predetermined locations on wafer
20   31.

        After wafer 35 arrives, LFOV camera 79 allows
the determination of the position of the wafer with
stages 39 in the position shown. After that, stages 39
allow movement of the objective to pattern locations and
25   measurement sites, where optical characteristics are
recorded with the help of spectrometers 61e and 63f.

        Alternatively, metrology station 19 includes
autofocus for objective 41.

        Alternatively, there is also a notch viewing
30   system like that provided in other process tool modules
for determining the precise wafer orientation and posi-
tion relative to the reflectometer instrument's objective
lens 41. The orientation of the pattern in the LFOV
image can be determined using pattern recognition soft-
35   ware, such as PatMax by Cognex Corporation. The location
of the center of a wafer is preferably determined by
moving the SFOV so as to image part or all of the curved
edge of the wafer, using the images, so obtained to cal-

culate the center position. Further, calibration marks
may be incorporated into the wafer support (not shown in
Fig. 3) to provide a reference for use in focusing when
the wafer is not present. For example, the very edge of
5   the top of one or more of the support points in the 3-
point wafer support can be used to determine the distance
to the measurement optics. This information, when com-
bined with wafer thickness information, can be used to
calculate the location of the wafer surface and control
10   adjustment of a 2-stage associated with either in the
optics assembly or the wafer support until the wafer is
in focus.

The optical measurement station would also
include a data acquisition and processing system, some or
15   all of which might be located outside of the process tool
module. In such a system, the measured reflected inten-
sity spectrum from a spectroreflectometer of pattern
features on the wafer or other like data from another
type of optical measurement, such as, beam profile
20   reflectometry, ellipsometry or polarimetry data, may be
digitized, possibly modified computationally, e.g., for
calibration, to become a measured characteristic used for
analysis. Analysis may include searching a library of
precomputed characteristics to find a best match or any
25   of the other scatterometry techniques described above..
The use of two measurement channels, one being a monitor
channel 61 and the other being the sample channel 63, and
the use of monolithic spectrometers 61e and 63f compen-
sate, e.g., for fluctuations or changes in the light
30   source and for temperature induced drifts. The objective
lens system 41 is part of an optical system with a low
numerical aperture (0.1 or less) to simplify the calcula-
tion of optical characteristics based on a single dif-
fracted order, and so that the system is less sensitive
35   to focus when observing the topographic patterned surface
of the wafer and to compensate for any wafer shapes devi-
ations while on the three-point support. Alternatively,

-18-

an autofocus system may adjust the distance between the objective and wafer.

Beamsplitter 59 is a inconel-coated fused silica plate. Alternatively, a multilayer dielectric or metal/dielectric hybrid coating may be used but with reduced efficiency over the combined UV and visible wavelength range. These other coatings also have the problem that they introduce more unwanted polarization in the beam. A cube beamsplitter may be used in place of the plate, but the plate has a particular advantage for UV systems since it uses no optical cement (as in the cube) that may deteriorate in UV light.

In some cases, the low NA desired for scatterometry may cause the area on the sample from which light is collected to become larger due to diffraction effects. There are two possible improvements to the optics in figure 3 that can be made. One is to make the system a confocal microscope-based system. Another is to place an apodizer near the aperture stop of the objective. These two improvements may be used together or separately.

In general, a confocal microscope projects a pinhole onto the sample being inspected or measured, the combined image of the sample and pinhole are then projected onto a second pinhole thereby allowing the microscope to collect light from an area on the sample smaller than diffraction would otherwise allow.

Figure 4 is detailed view of components that replace lens 55 in figure 3 to convert the system in figure 3 to a confocal microscope-based system. In figures 3 and 4, parallel rays 107a and 107b that exit fiber 101 are focused to reflective pinhole 103 by ball lens 102. Rays 107a and 107b are then collimated by lenses 106a and 106b. The rays 107a and 107b are then focused on the wafer 31 forming an image of the pinhole 103 on wafer 31.   The image of the pinhole 103 on the wafer 31 should be slightly larger than the measurement spot used to collect light determined by the size of pinhole 43 and

the magnification of the lens system comprising objective
41 and lens 63d. Reducing the size of pinhole 103 has
the desired effect of reducing the spotsize, but it also
has the undesired effect of decreasing the depth of focus
5   on the wafer 31. The size is chosen to balance these two
effects.

        Another consequence of the pinhole 103 is that
it blocks the light illuminating the rest of the field of
view that is used for pattern recognition. To provide
10   field illumination, the pinhole 103 is etched in a re-
flective coating that can allow light from field illumi-
nation optics 105 to reflect off its face. The shutter
104 is open when the field must be illuminated for pat-
tern recognition and closed for measurements. The field
15   illumination optics 105 are arranged such that its exit
pupil (not shown) is imaged near the wafer plane 31, and
the light source (not shown) is imaged just after mirror
57.

        An apodizer is an aperture with a gradually
20   varying transmission that serves to remove the diffrac-
tion rings from the point spread function and reduces the
effective spot size of the instrument. Ideally, the
apodizer should produce a Gaussian intensity profile in
the transmitted beam, but in practice any smooth profile
25   that varies from dark to light will nearly as good. The
goal is to eliminate as much as possible of the high end
of the spatial frequency spectrum of the profile. The
apodizer can also be a graded reflective surface

        To avoid or reduce vignetting, the apodizer
30   should be placed at or near the aperture stop for the
optical system. Figure 4 is a detail from figure 3 show-
ing four possible positions for the apodizer.

        In Fig. 4, position 101 is closest to the ob-
jective stop, but it does not introduce some of the ad-
35   vantages of other positions. Since the light travels
through the apodizer twice at this point, the optical
density profile has to be multiplied by 0.5 compared to
the other positions.

Position 102 is also close to the objective
aperture, but it also reduces the sensitivity of the
system to sample tilt. This is true whenever the stops
for illumination and collection beams have slightly dif-
5   ferent sizes. Position 102 is also to best location for
an ordinary system aperture stop to reduce the collected
NA from the wafer.

Position 103 is the best place for a reflective
apodizer. Since it is at 45 deg. it must be elongated in
10   one direction.

Position 104 is in many ways similar to posi-
tion 102 , but is probably less desirable because it
places a moving aperture in the monitor channel path (not
shown above) that may affect its reading.

15   In the preferred embodiment, the processor
calculates the optical characteristic from optical spec-
tra, and then selects a set of measurement parameters
from a library for the structure of interest based on the
best fit between the measured characteristic and a model
20   characteristic in the library. The library has been
calculated before the measurements are made on the de-
sired wafer, with appropriate parameters.

With the measured spectrum as the basis of the
optical characteristic, the best match being associated
25   with a set of one or more optical and/or geometric param-
eters (width, height, profile, refractive index, etc.) of
the structure on the illuminated area of the wafer. Once
such parameters have been determined, and possibly modi-
fied or transformed, these measurement results can be
30   used for process control of subsequent steps on that
wafer by the processing stations in the process tool or
for process control of any of the preceding process steps
for subsequent wafers or for fault detection to avoid
wasted processing or wasted wafers. Adjustments to pro-
35   cess tool recipe parameter are calculated based on a
model of the process and deviations of the measured
parameters from the target parameters. Integration of
the measurement instrument into the process tool speeds

-21-

wafer manufacture and allows short loop wafer process
control.

In Fig. 3 the coordinate axes x, y and z, are
shown for convenience. In practice the axes may be ro-
5   tated to a convenient position. While a preferred em-
bodiment has been described in detail, many alternative
embodiments are possible within the scope of the current
invention.

Claims

1.   A wafer measurement system for use within a wafer
process tool, comprising:

5   a wafer handler associated with the wafer
process tool for feeding wafers between a cassette and
any one or more of a plurality of stations of the wafer
process tool;

               a wafer measurement station forming one of the

10   stations of the wafer process tool, the measurement
station having a wafer support in communication with the
wafer handler, the measurement station also having
therein an optical measurement system forming a
scatterometry instrument that is moveable by a stage to

15   specified locations over the wafer support, the optical
measurement system optically coupled to a light source to
direct a light beam as a spot onto patterned features of
a wafer surface on the wafer support, wherein the light
beam is characterized by a spot size that is larger at

20   the wafer surface than a periodicity of the patterned
features, the head also having a light collector
associated with a detector whereby illuminated features
on the wafer yield characteristic optical signatures with
independent optical parameters in the signatures

25   including one or more of wavelength, incidence angle,
and altitude and azimuthal collection angles; and

               a data processor analyzing the characteristic
signatures of a wafer using a scattering model for
possible periodic structures on a wafer to obtain a

30   measure of the patterned features on the wafer so that a
process carried out by the wafer process tool can be
analyzed.

35   2.   The apparatus of claim 1 wherein the optical
measurement system includes an objective lens imaging
light from a spot on the wafer.

-23-

3. The apparatus of claim 2 wherein the optical measurement system forms a low numerical aperture (NA) system with an NA < 0.4 for optimum scatterometry.

5

4. The apparatus of claim 2 wherein the optical measurement system includes a pinhole aperture associated with the light collector receiving light from the wafer, with the objective lens imaging light traveling in

10   opposite directions, the pinhole aperture maintaining a fixed optical relationship to the objective lens as it moves.

15   5.   The apparatus of claim 2 wherein the movable optical measurement system comprises a confocal microscope-based measurement system.

20   6.   The apparatus of claim 2 wherein the measurement system further includes an apodizer located near the objective aperture stop of the microscope-based system.

25   7. The apparatus of claim 2 wherein illumination and collection paths of the microscope-based system separate at an inconel plate beamsplitter.

30   8.   The apparatus of claim 1 wherein the light beam incident on the wafer is substantially unpolarized and the optical measurement system is substantially polarization insensitive.

-24-

9. The apparatus of claim 1 wherein the wafer handler
feeds wafers into the wafer measurement station with a
unspecified wafer orientation relative to the optical
measurement system.

5

10. The apparatus of claim 1 wherein the optical
measurement head directs the light beam at normal
incidence onto the wafer surface.

10

11. The apparatus of claim 1 wherein the measure of
patterned features obtained by the data processor
·includes at least one dimension of lateral or vertical

15   geometric structure of features on the wafer.

12. The apparatus of claim 11 wherein the measure of
patterned features include line width and profile of

20   features of the wafer.

13. The apparatus of claim 12 wherein the profile of
pattern features is characterized by a feature height or

25   depth that may be variable with lateral position across
the features, the scattering model used by the data
processor taking such variable feature height or depth
dependence on lateral position into account.

30

14. The apparatus of claim 1 wherein the measure of
patterned features obtained by the data processor
includes any one or more of: overlay, erosion, residue,
trench depth, film thickness, contact hole shape and

35   size, open or closed state of contacts, and line edge
roughness.

-25-

15. The apparatus of claim 1 wherein the measurement
station includes an optical absorber positioned to one
side of the wafer support to provide a reference zero
reflectance measure for bright background measurement.

16. The apparatus of claim 1 further comprising an x-y
stage driving the optical measurement system, the wafer
support holding the wafer stationary within the wafer
measurement station.

17. The apparatus of claim 1 wherein the wafer support
is capable of moving a wafer in at least one dimension.

18. The apparatus of claim 17 wherein the wafer support
is rotatable to any of a plurality of angular
orientations (q) of wafer features relative to the
measurement head without (x,y) translation of the wafer,
and a linear stage drives the optical measurement system
relative to a radial position (r) of the wafer.

19. The apparatus of claim 17 wherein the wafer support
provides (x,y) translation of a wafer.

20. The apparatus of claim 17 wherein the wafer support
is tiltable to any of a plurality of incidence angles of
said beam onto said wafer surface.

21. The apparatus of claim 1 wherein the wafer support
provides at least a 3-pin wafer contact.

-26-

22.   The apparatus of claim 1 wherein the wafer support
comprises a vacuum chuck.

5   23.   The apparatus of claim 1 wherein the measurement
station includes a window located between the measurement
system and the wafer support to isolate a wafer from
potential contamination by the movable optical system.

10

24.   The apparatus of claim 23 wherein the measurement
station is otherwise unsealed from the process tool
environment.

15

25.   The apparatus of claim 23 wherein the window is
removable to permit cleaning and maintenance of the
optical measurement system and a stage for moving the
system.

20

26.   A wafer measurement method for cooperative use with
a wafer process tool of the type having a wafer handler
associated with a cassette of wafers, comprising:

25   within the wafer process tool after completion
of any of one or more process steps carried out in
processing stations of the process tool, receiving in an
integrated measuring station of the process tool a wafer
from a wafer handler associated with the process tool

30   without first transferring wafers out of the process tool
to another cassette or cassette loading station, and
depositing the wafer at an unspecified orientation in the
measurement station relative to a moveable optical
measurement system;

35   moving an optical measurement system to a
plurality of locations over the wafer;

directing a beam of light normally onto the
wafer surface as a light spot at each of said plurality
of locations, the light spot characterized by a spot size
that is larger at the wafer surface than a periodicity of
5   pattern features on the wafer;
        detecting light reflected from the wafer
surface to obtain data for an optical characteristic of
surface pattern features of the wafer at said plurality
of locations; and
10   analyzing the optical characteristic data using
a scattering model of possible periodic structures on a
wafer to obtain a measure of critical dimensions of the
surface pattern features on the wafer.

15

27. The method of claim 26 further defined by
sequentially measuring reflectance data for a plurality
wafers received from the wafer process tool.

Fig. 1

Fig. 2

Figure 3

Figure 4

Figure 5